

Technical Specifications

NVR

Model	GV-NVR (GV)		GV-NVR	
Video Input	4, 8, 12, 16		1, 2, 4, 6, 8, 10, 12, 16	
Audio Input	4, 8, 12, 16		1, 2, 4, 6, 8, 10, 12, 16	
Recording Rate	Maximum 480 fps at D1 resolution			
IP Camera	GeoVision	GV-IPCAM 1.3M, GV-Video Server, GV-Compact DVR	Arecont Vision	AV1300, AV2100, AV3100, AV5100
			AXIS	AXIS 206, AXIS 207, AXIS 207W, AXIS 207MW, AXIS 210, AXIS 211, AXIS 211A, *AXIS 212 PTZ, *AXIS 213 PTZ, *AXIS 214 PTZ, AXIS 216FD, AXIS 216FD-V, AXIS 221, AXIS 223M, AXIS 225FD, AXIS 231D+, AXIS 232D+, AXIS 233D
			GeoVision	GV-IPCAM 1.3M, GV-Video Server, GV-Compact DVR
			IQinvision	IQeye301, IQeye302, *IQeye510, *IQeye511, IQeye701, IQeye702
			JVC	VN-C20U, VN-C205U, VN-C215U, *VN-C625U, *VN-C655U
			Mobotix	Mobotix_M12
			Panasonic	BB-HCM110, *BB-HCM311, *BB-HCM331, BB-HCM371, *BB-HCM381, *BB-HCM403, *BB-HCE481A, BL-C10, BL-C30
		SONY	SNC-CS10, SNC-CS11, SNC-CS50N, SNC-CS50P, SNC-DF40N, SNC-DF40P, SNC-DF50N, SNC-DF50P, SNC-DF70N, SNC-DF70P, SNC-DF80N, SNC-DF80P, SNC-P1, *SNC-P5, *SNC-RX550N, *SNC-RX550P, *SNC-RZ25N, *SNC-RZ25P, *SNC-RZ50N, *SNC-RZ50P	
Networking	TCP / IP, LAN, WAN, Internet, Modem Dial-up, Modem-to-Modem, ISDN			
Backup Device	HDD, NAS, CD-R / R-W, DVD±R / ±RW, DVD±R (DL), ZIP, JAZ, Blu-ray			
Operating System	Windows 2000, Windows XP, Windows Server 2003, Windows Vista			
Language	Czech / Danish / Dutch (Netherlands) / English / French / German / Hebrew / Hungarian / Italian / Japanese / Polish / Portuguese / Russian / Serbian / Simplified Chinese / Spanish / Traditional Chinese / Thai			

* IP Cam with PTZ control